

## Fiche technique

07/03/2016

**LOT-XTD22A-12-Z1**

**POUSSOIR DE SECURITE A CLIPSER 2 x NO**



POUSSOIR DE SECURITE A CLIPSER.

2 CONTACTS N/O FUGITIF.

-1:16,5Amp/400Vac(BORNES 1 & 2).

-1:500mA/30Vdc(BORNES 3 & 4).

CONNEXION COSSE FASTON MALE 6,3.

DIM:30 x 32 x 12mm.

FAB.:SAIA-BURGESS ELECTRONICS REF.:XTD22A12Z1.